Chorum 80-S









English Specification

Pedal (8 stops)		Great (11 stops)		Swell (14 stops)		Choir (11 stops	Choir (11 stops)	
Contra Violone	32	Open Diapason	8	Bourdon	16	Open Diapason	8	
Open Wood	16	Stopped Diapasor	n 8	Open Diapason	8	Gedackt	8	
Bourdon	16	Gamba	8	Rohr Flute	8	Gemshorn	4	
Principal	8	Claribel Flute	8	Salicional	8	Lieblich	4	
Bass Flute	8	Principal	4	Voix Celeste	8	Nazard	2.2/3	
Choral Bass	4	Harmonic Flute	4	Principal	4	Flageolet	2	
Trombone	16	Twelfth	2.2/3	Stopped Flute	4	Tierce	1.3/5	
Trumpet	8	Fifteenth	2	Fifteenth	2	Larigot	1.1/3	
		Full Mixture	IV	Sesquialtera	Ш	Mixture	III	
		Double Trumpet	8	Mixture	IV	Clarinet	8	
		Trumpet	8	Contra Fagotto	16	Tuba	8	
				Cornopean	8			
				Oboe	8			
				Clarion	4			
Great to pedal		Tremulant		Tremulant		Tremulant		
Swell to pedal		Swell to Great				Swell to Choir		
Choir to pedal		Choir to Great						

Chorum 80-S





Principal Features

- 3 x 61 note tracker touch keyboards, velocity sensitive for midi and orchestral voices
- 30 note radiating concave pedal board
- 44 tilt tab speaking stops with12 orchestral voices
- 4 pre-set organ styles (English, Baroque 1, Baroque 2 and Romantic)
- 17 alternative temperaments

Playing Aids

- Choir expression pedal (can be set as crescendo)
- Swell expression pedal
- 9 toe pistons including 6 coupler reversers
- 6 divisional pistons to Sw/Gt/Ch and Pedal
- 6 general pistons
- 16 capture memories
- Auto pedal and Gt/Ped enclosed pistons
- Keyboard inversion and Transposer -6/+5 semitones
- Fully adjustable Tremulants (speed and depth)

Display and Software Features

 Backlight display with 6 button control to access all organ choice and set up features

Dimensions and Finishes

- Dark or light oak simulated wood veneer
- 125cm (W) 116cm (H) 62cm (D) 114cm with pedal board
- Weight 119 Kg

Audio System and Sound Management

- Independent volume adjustment of each division
- Independent volume adjustment of each stop
- 5 internal speakers 2 full range, 2 tweeters and 1 woofer
- 2 x 60 watt internal amplifiers and 1 x 100 watt amplifier
- Internal 7 band graphic equaliser
- Fully adjustable reverberation with 8 levels
- Stereo headphone output socket
- External outputs to 2 channels
- MIDI in-out-through